




# Connector Views

## 110. DRL and Low Beam Cut Relays (Canada)

- Under left side of dash
- On dashboard wire harness B (left branch)



### ① Low Beam Cut Relay:

- 1 RED/WHT (Low beam control)
- 2 —
- 3 RED/BLK (High beam control)
- 4 RED/YEL (Dimmer switch input)
- 5 RED/BLU (High beam control)

### ② DRL Relay:

- 1 RED/YEL (Low beam control)
- 2 RED (Fuse 10 – Under-dash)
- 3 RED/BLK (High beam control)
- 4 —
- 5 RED/BLU (High beam control)