12/16/24, 9:07 PM

| Last Modified: 12-04-2024          | 6.11:8.1.0                 | <b>Doc ID:</b> RM10000002BEHS                |
|------------------------------------|----------------------------|--|
| Model Year Start: 2023             | Model: Prius Prime         | <b>Prod Date Range:</b> [03/2023 - ]         |
| Title: HYBRID / BATTERY CONTROL    | : PLUG-IN CHARGE CONTR     | OL SYSTEM (for PHEV Model): P1CA400; Charger |
| Pre-charging Malfunction; 2023 - 2 | 024 MY Prius Prime [03/202 | 3 - ]  |

| DTC | P1CA400 | Charger Pre-charging Malfunction |
|-----|---------|----------------------------------|
|-----|---------|----------------------------------|

## **DESCRIPTION**

The charge control ECU built into the electric vehicle charger assembly monitors its internal operation. If it detects a precharge malfunction, it stores a DTC. When this DTC is output, replace the electric vehicle charger assembly.

| DTC NO. | DETECTION<br>ITEM                       | DTC DETECTION<br>CONDITION                     | TROUBLE<br>AREA | MIL   | WARNING<br>INDICATE            | DTC<br>OUTPUT<br>FROM | PRIORITY | NOTE                  |
|---------|---|--|-----------------|-------|--------------------------------|-----------------------|----------|-----------------------|
| II      | charger Pre-<br>charging<br>Malfunction | has not been completed for a certain amount of | Electric        | Comes | Master<br>Warning:<br>Comes on | Plug-in<br>Control    |          | SAE<br>Code:<br>POD5C |

## **MONITOR DESCRIPTION**

The charge control ECU built into the electric vehicle charger assembly monitors its internal operation. If it detects a precharge malfunction, it illuminates the MIL and stores a DTC.

## **MONITOR STRATEGY**

| Related DTCs                | P0D5C: Battery Charger Hybrid/EV Battery Output Power Performance |  |
|-----------------------------|---|--|
| Required sensors/components | Electric vehicle charger assembly                                 |  |
| Frequency of operation      | Continuous  |  |
| Duration                    | TMC's intellectual property                                       |  |
| MIL operation               | 1 charging cycle  |  |
| Sequence of operation       | None  |  |

# TYPICAL ENABLING CONDITIONS

| The monitor will run whenever the following DTCs are not stored | TMC's intellectual property |  |
|---|-----------------------------|--|
| Other conditions belong to TMC's intellectual property          | -                           |  |

## **TYPICAL MALFUNCTION THRESHOLDS**

| TMC's intellectual property | - |  |
|-----------------------------|---|--|
|-----------------------------|---|--|

### **COMPONENT OPERATING RANGE**

| Electric vehicle charger assembly | DTC P1CA400 is not detected |
|-----------------------------------|-----------------------------|
|-----------------------------------|-----------------------------|

## **CONFIRMATION DRIVING PATTERN**

#### HINT:

• After repair has been completed, clear the DTC and then check that the vehicle has returned to normal by performing the following All Readiness check procedure.

Click here NFO

• When clearing the permanent DTCs, refer to the "CLEAR PERMANENT DTC" procedure.

Click here

- 1. Clear the DTCs (even if no DTCs are stored, perform the clear DTC procedure).
- 2. Enter the following menus: Powertrain / Hybrid Control / Data List.
- 3. Check that "Hybrid/EV Battery SOC" shows 70% or less.
- 4. Turn the ignition switch off and wait for 2 minutes or more.
- 5. Connect the electric vehicle charger cable assembly, and plug-in charge the vehicle for 30 seconds or more. [\*1]
- 6. Disconnect the electric vehicle charger cable assembly and wait for 10 seconds or more. [\*2]

#### HINT:

[\*1] to [\*2]: Normal judgment procedure.

The normal judgment procedure is used to complete DTC judgment and also used when clearing permanent DTCs.

- 7. Enter the following menus: Powertrain / Plug-in Control / Utility / All Readiness.
- 8. Check the DTC judgment result.

### HINT:

- If the judgment result shows NORMAL, the system is normal.
- If the judgment result shows ABNORMAL, the system has a malfunction.
- If the judgment result shows INCOMPLETE or N/A, perform the normal judgment procedure again.

## **PROCEDURE**

1. REPLACE ELECTRIC VEHICLE CHARGER ASSEMBLY

### HINT:

Click here

NEXT COMPLETED



**Фтоуота**